2 Drawer Phone Dropbox Customer Instructions

SKU GFSA-DB-2

GENERATION FARADAY

MADE BY MISSION DARKNESS



Two drawers, one opens at a time



36 numbered slots per drawer



Combination lock and master key

Getting started checklist

PRODUCT SET-UP

- [ ] Unbox and place the unit on a flat, level surface.
- [ ] Lock the caster wheels and keep them locked while in use.
- [ ] Change the combination from the factory 1-1-1-1 (page 2).
- [ ] Train staff and students on your phone policy.

GENERATION FARADAY APP

- [ ] Download the app and create your account.
- [ ] Invite users, then upload your students.
- [ ] Scan the RFID tag or search the serial number to pull up cabinet details.
- [ ] Assign students to numbered drawer slots.

Daily Use

- Open one drawer at a time; the other stays locked.
- Load phones into the numbered slots, 36 per drawer.
- Close flush, then lock both side latches.

Never

- Force a second drawer open or bypass the interlock.
- Sit or stand on the unit.
- Open drawers while the unit is moving.

Care

- Wipe with a soft cloth and mild detergent.
- No abrasive cleaners or solvents.
- Signal blocking weak? Replace the gasket seals around the door with the included set.
- Foam damaged? Contact us for replacement drawer foams.

Signal Blocking

Close the door fully and engage both side latches. Sealed, the unit blocks cellular, Wi-Fi, Bluetooth, and GPS , phones stay unreachable until you unlock it.


1-YEAR WARRANTY | Covers manufacturing defects. Contact us for replacement parts or service.

Combination Lock Operating Instructions


GENERATION FARADAY
MADE BY MISSION DARKNESS

Lock position | **Unlock position** | **Change codes position**

1 Lock and unlock



1. Enter correct code (factory setting: 1-1-1-1), then rotate lock 90 degrees lockwise to "🔒"




2. After using, rotate lock body 90 degrees (counter clockwise) to lock, the code will go back to 0-0-0-0 automatically.


TIP

Use the master key to lock or unlock without the combination.


2 Change new codes



1. Enter correct (current) code.




2. Rotate lock body 10 degrees counterclockwise to "△" position.




3. Turn dials to set any 4-digit code, then rotate the lock body to "🔒" position to complete new code setting.

3 Find current codes



1. Insert master key and rotate 90 degrees.



2. Turn the dials from top to bottom until they stop turning, the last numbers displayed are the current codes. Pull out the key to open.

ONBOARDING & SUPPORT

We'll help you roll out

Questions on operation, parts, or service? Your Generation Faraday contact is ready to help.

EMAIL
support@generationfaraday.com

GET IN TOUCH
generationfaraday.com/get-in-touch